Specifications

Eaton 204980

Eaton Moeller® series STN Control transformer, 0.25 kVA, Rated input voltage 400± 5 % V, Rated output voltage 230 V

General specifications	
PRODUCT NAME	Eaton Moeller® series STN Control transformer
CATALOG NUMBER	204980
MODEL CODE	STN0,25(400/230)
EAN	4015082049805
PRODUCT LENGTH/DEPTH	83 mm
PRODUCT HEIGHT	112 mm
PRODUCT WIDTH	106 mm
PRODUCT WEIGHT	2.996 kg
CERTIFICATIONS	CE CSA-C22.2 No. 66 UL Recognized Certified by UL for use in Canada UL5085-1 UL 5085-2 CSA-C22.2 No. 66.1-06 CSA-C22.2 No. 66.2-06 UL Category Control No.: XPTQ2, XPTQ8 UL 506 VDE 0113, VDE 0100 Part 410 VDE 0570 Part 2-2 IEC/EN 61558-2-2 UL report applies to both US and Canada IEC/EN 60204-1, ÖVE-EN 13 UL File No.: E167225
CATALOG NOTES	Electrical characteristics: all details for no-load loss, short-circuit loss (copper losses), short-circuit voltage and efficiency values relate to a temperature of 20 °C



GLOBAL CATALOG

204980

Product specifications

ТҮРЕ	Single-phase STN control transformers
FEATURES	Separate windings Fully Vacuum-impregnated
10.10 TEMPERATURE RISE	The panel builder is responsible for the temperature rise calculation. Eaton will provide heat dissipation data for the devices.
10.11 SHORT-CIRCUIT RATING	Is the panel builder's responsibility. The specifications for the switchgear must be observed.
10.12 ELECTROMAGNETIC COMPATIBILITY	Is the panel builder's responsibility. The specifications for the switchgear must be observed.
10.13 MECHANICAL FUNCTION	The device meets the requirements, provided the information in the instruction leaflet (IL) is observed.
10.2.2 CORROSION RESISTANCE	Meets the product standard's requirements.
10.2.3.1 VERIFICATION OF THERMAL STABILITY OF ENCLOSURES	Meets the product standard's requirements.
10.2.3.2 VERIFICATION OF RESISTANCE OF INSULATING MATERIALS TO NORMAL HEAT	Meets the product standard's requirements.
10.2.3.3 RESIST. OF INSUL. MAT. TO ABNORMAL HEAT/FIRE BY INTERNAL ELECT. EFFECTS	Meets the product standard's requirements.
10.2.4 RESISTANCE TO ULTRA-VIOLET (UV) RADIATION	Meets the product standard's requirements.
10.2.5 LIFTING	Does not apply, since the entire switchgear needs to be evaluated.
10.2.6 MECHANICAL IMPACT	Does not apply, since the entire switchgear needs to be evaluated.
10.2.7 INSCRIPTIONS	Meets the product

Resources

APPLICATION NOTES	<u>eaton-transformer-stz-sti-</u> <u>stn-dtz-uti-ap009002-en-</u> <u>us.pdf</u>
BROCHURES	<u>eaton-transformers-</u> <u>brochure-br009002en-en-</u> <u>us.pdf</u>
CATALOGS	eaton-product-overview- for-machinery-catalogue- ca08103003zen-en-us.pdf
DECLARATIONS OF CONFORMITY	DA-DC-00004420.pdf DA-DC-00004448.pdf
DRAWINGS	<u>eaton-general-control-stn-</u> <u>control-transformer-</u> <u>dimensions-006.eps</u>
ECAD MODEL	ETN.204980.edz
MCAD MODEL	DA-CD-stn0_25 DA-CS-stn0_25
SPECIFICATIONS AND DATASHEETS	Eaton Specification Sheet - 204980
SYSTEM OVERVIEW	eaton-general-diagram-sti- control-transformer- explosion-drawing.eps

	standardle requirements
	standard's requirements.
10.3 DEGREE OF PROTECTION OF ASSEMBLIES	Does not apply, since the entire switchgear needs to be evaluated.
10.4 CLEARANCES AND CREEPAGE DISTANCES	Meets the product standard's requirements.
10.5 PROTECTION AGAINST ELECTRIC SHOCK	Does not apply, since the entire switchgear needs to be evaluated.
10.6 INCORPORATION OF SWITCHING DEVICES AND COMPONENTS	Does not apply, since the entire switchgear needs to be evaluated.
10.7 INTERNAL ELECTRICAL CIRCUITS AND CONNECTIONS	ls the panel builder's responsibility.
10.8 CONNECTIONS FOR EXTERNAL CONDUCTORS	ls the panel builder's responsibility.
10.9.2 POWER- FREQUENCY ELECTRIC STRENGTH	ls the panel builder's responsibility.
10.9.3 IMPULSE WITHSTAND VOLTAGE	ls the panel builder's responsibility.
10.9.4 TESTING OF ENCLOSURES MADE OF INSULATING MATERIAL	ls the panel builder's responsibility.
AMBIENT OPERATING TEMPERATURE - MAX	40 °C
AMBIENT OPERATING TEMPERATURE - MIN	-25 °C
APPARENT POWER	250 VA
EQUIPMENT HEAT DISSIPATION, CURRENT- DEPENDENT PVID	0 W
HEAT DISSIPATION CAPACITY PDISS	0 W
HEAT DISSIPATION PER POLE, CURRENT- DEPENDENT PVID	0 W
NO-LOAD LOSSES	9 W
PRIMARY VOLTAGE 1 - MAX	400 V
PRIMARY VOLTAGE 1 - MIN	400 V
PRIMARY VOLTAGE 10 - MAX	0 V
PRIMARY VOLTAGE 10 - MIN	0 V
PRIMARY VOLTAGE 2 -	0 V

МАХ	
PRIMARY VOLTAGE 2 - MIN	0 V
PRIMARY VOLTAGE 3 - MAX	0 V
PRIMARY VOLTAGE 3 - MIN	0 V
PRIMARY VOLTAGE 4 - MAX	0 V
PRIMARY VOLTAGE 4 - MIN	0 V
PRIMARY VOLTAGE 5 - MAX	0 V
PRIMARY VOLTAGE 5 - MIN	0 V
PRIMARY VOLTAGE 6 - MAX	0 V
CONDUCTOR MATERIAL	Copper
DEGREE OF PROTECTION	IP00
CONNECTION LUG	Yes for > 115 A
CONNECTION TYPE	Terminations, < 115 A
DUTY FACTOR	100 %
INSULATION MATERIAL TYPE (IEC 85)	В
EFFICIENCY	90 %
RELATIVE SHORT-CIRCUIT VOLTAGE	6.3 %
SUITABLE FOR	Branch circuits, (UL/CSA)
INSULATION CLASS	В
PRIMARY TAPPING	± 5 %
PRIMARY VOLTAGE 6 - MIN	0 V
PRIMARY VOLTAGE 7 - MAX	0 V
PRIMARY VOLTAGE 7 - MIN	0 V
PRIMARY VOLTAGE 8 - MAX	0 V
PRIMARY VOLTAGE 8 - MIN	0 V
PRIMARY VOLTAGE 9 - MAX	0 V
PRIMARY VOLTAGE 9 - MIN	0 V
RATED FREQUENCY - MAX	60 Hz

RATED FREQUENCY - MIN50 HzRATED OPERATIONAL CURRENT FOR SPECIFIED HEAT DISSIPATION (IN)0.ARATED POWER0.25 VASECONDARY VOLTAGE 1 MAX230 VSECONDARY VOLTAGE 1 - MAX0 VSECONDARY VOLTAGE 2 - MIN0 VSECONDARY VOLTAGE 2 MIN0 VSECONDARY VOLTAGE 2 MIN0 VSECONDARY VOLTAGE 2 MIN0 VSECONDARY VOLTAGE 3 MIN0 VSECONDARY VOLTAGE 4 MIN0 VSECONDARY VOLTAGE 5 MIN0 VSECONDARY VOLTAGE 4 MIN0 VSECONDARY VOLTAGE 5 MAX0 VSECONDARY VOLTAGE 5 MAX0 VSECONDARY VOLTAGE 5 MAX0 VSECONDARY VOLTAGE 5 MIN0 VSEC		
CURRENT FOR SPECIFIED HEAT DISSIPATION (IN)0 ARATED POWER0.25 VASECONDARY VOLTAGE 1 MIN230 VSECONDARY VOLTAGE 10 - MAX0 VSECONDARY VOLTAGE 10 - MAX0 VSECONDARY VOLTAGE 20 MAX0 VSECONDARY VOLTAGE 20 MAX0 VSECONDARY VOLTAGE 20 MAX0 VSECONDARY VOLTAGE 20 MAX0 VSECONDARY VOLTAGE 30 MIN0 VSECONDARY VOLTAGE 40 MAX0 VSECONDARY VOLTAGE 50 MAX0 VSECONDARY VOLTAGE 51 MIN0 VSECONDARY VOLTAGE 52 MIN0 VSECONDARY VOLTAGE 51 MIN0 V </th <th>RATED FREQUENCY - MIN</th> <th>50 Hz</th>	RATED FREQUENCY - MIN	50 Hz
SECONDARY VOLTAGE 1230 VSECONDARY VOLTAGE 1230 VSECONDARY VOLTAGE 100 V-MAX0 VSECONDARY VOLTAGE 2-0 VSECONDARY VOLTAGE 3-0 VSECONDARY VOLTAGE 4-0 VSECONDARY VOLTAGE 4-0 VSECONDARY VOLTAGE 4-0 VSECONDARY VOLTAGE 4-0 VSECONDARY VOLTAGE 5-0 VSECONDARY VOLTAGE 5-0 VSECONDARY VOLTAGE 6-0 VSECONDARY VOLTAGE 7-0 VSECONDARY VOLTAGE 7-0 VSECONDARY VOLTAGE 8-0 VSECONDARY VOLTAGE 8-0 VSECONDARY VOLTAGE 8-0 VSECONDARY VOLTAGE 9-0 V </th <th>CURRENT FOR SPECIFIED</th> <th>0 A</th>	CURRENT FOR SPECIFIED	0 A
MAX230 VSECONDARY VOLTAGE 1 - MAX230 VSECONDARY VOLTAGE 10 - MIN0 VSECONDARY VOLTAGE 2- MAX0 VSECONDARY VOLTAGE 2- MAX0 VSECONDARY VOLTAGE 2- MIN0 VSECONDARY VOLTAGE 2- MAX0 VSECONDARY VOLTAGE 3- MAX0 VSECONDARY VOLTAGE 4- MAX0 VSECONDARY VOLTAGE 4- MAX0 VSECONDARY VOLTAGE 4- MAX0 VSECONDARY VOLTAGE 4- MAX0 VSECONDARY VOLTAGE 4- MIN0 VSECONDARY VOLTAGE 4- MIN0 VSECONDARY VOLTAGE 4- MIN0 VSECONDARY VOLTAGE 4- MAX0 VSECONDARY VOLTAGE	RATED POWER	0.25 VA
MIN230 VSECONDARY VOLTAGE 10 - MIN0 VSECONDARY VOLTAGE 20 MAX0 VSECONDARY VOLTAGE 20 MAX0 VSECONDARY VOLTAGE 20 MAX0 VSECONDARY VOLTAGE 30 MAX0 VSECONDARY VOLTAGE 40 MAX0 VSECONDARY VOLTAGE 41 MAX0 VSECONDARY VOLTAGE 42 MAX0 VSECONDARY VOLTAGE 42 MAX0 VSECONDARY VOLTAGE 50 MAX0 VSECONDARY VOLTAGE 51 MAX0 VSECONDARY VOLTAGE 61 MAX0 VSECONDARY VOLTAGE 62 MAX0 VSECONDARY VOLTAGE 63 MAX0 VSECONDARY VOLTAGE 72 MAX0 VSECONDARY VOLTAGE 73 MAX0 VSECONDARY VOLTAGE 74 MAX0 VSECONDARY VOLTAGE 75 MAX0 V		230 V
· MAX0 VSECONDARY VOLTAGE 10 · MIN0 VSECONDARY VOLTAGE 2- MAX0 VSECONDARY VOLTAGE 3- MAX0 VSECONDARY VOLTAGE 3- MAX0 VSECONDARY VOLTAGE 4- MAX0 VSECONDARY VOLTAGE 4- MIN0 VSECONDARY VOLTAGE 4- MIN0 VSECONDARY VOLTAGE 5- MAX0 VSECONDARY VOLTAGE 6- MAX0 VSECONDARY VOLTAGE 6- MAX0 VSECONDARY VOLTAGE 6- MIN0 VSECONDARY VOLTAGE 6- MAX0 VSECONDARY VOLTAGE 6- MAX0 VSECONDARY VOLTAGE 6- MIN0 VSECONDARY VOLTAGE 7- MAX0 VSECONDARY VOLTAGE 8- MIN0 VSECONDARY VOLTAGE 8- MAX0 VSECONDARY VOLTAGE 9- MAX0 V		230 V
· MIN0 VSECONDARY VOLTAGE 2- MAX0 VSECONDARY VOLTAGE 2- MIN0 VSECONDARY VOLTAGE 3- MAX0 VSECONDARY VOLTAGE 4- MAX0 VSECONDARY VOLTAGE 4- MAX0 VPRODUCT CATEGORYSingle-phase control transformers STSECONDARY VOLTAGE 4- MIN0 VSECONDARY VOLTAGE 5- MAX0 VSECONDARY VOLTAGE 5- MAX0 VSECONDARY VOLTAGE 5- MAX0 VSECONDARY VOLTAGE 5- MAX0 VSECONDARY VOLTAGE 6- MIN0 VSECONDARY VOLTAGE 6- MIN0 VSECONDARY VOLTAGE 7- MAX0 VSECONDARY VOLTAGE 7- MAX0 VSECONDARY VOLTAGE 7- MAX0 VSECONDARY VOLTAGE 7- MAX0 VSECONDARY VOLTAGE 8- MAX0 VSECONDARY VOLTAGE 9- MAX0 VSECONDARY VOLTAGE 9- MAX0 V		0 V
MAX0 VSECONDARY VOLTAGE 2- MIN0 VSECONDARY VOLTAGE 3- MAX0 VSECONDARY VOLTAGE 3- MIN0 VSECONDARY VOLTAGE 4- MAX0 VPRODUCT CATEGORYSingle-phase control transformers STSECONDARY VOLTAGE 4 MIN0 VSECONDARY VOLTAGE 5 MAX0 VSECONDARY VOLTAGE 5 MIN0 VSECONDARY VOLTAGE 5 MIN0 VSECONDARY VOLTAGE 6 MIN0 VSECONDARY VOLTAGE 6 MIN0 VSECONDARY VOLTAGE 7 MAX0 VSECONDARY VOLTAGE 7 MIN0 VSECONDARY VOLTAGE 8 MIN0 VSECONDARY VOLTAGE 8 MIN0 VSECONDARY VOLTAGE 8 MIN0 VSECONDARY VOLTAGE 9 MAX0 V		0 V
MIN0 VSECONDARY VOLTAGE 3- MAX0 VSECONDARY VOLTAGE 3- MIN0 VSECONDARY VOLTAGE 4- MAX0 VPRODUCT CATEGORYSingle-phase control transformers STSECONDARY VOLTAGE 4- MIN0 VSECONDARY VOLTAGE 5- MAX0 VSECONDARY VOLTAGE 5- MIN0 VSECONDARY VOLTAGE 5- MIN0 VSECONDARY VOLTAGE 6- MAX0 VSECONDARY VOLTAGE 6- MIN0 VSECONDARY VOLTAGE 7- MIN0 VSECONDARY VOLTAGE 7- MIN0 VSECONDARY VOLTAGE 7- MIN0 VSECONDARY VOLTAGE 8- MAX0 VSECONDARY VOLTAGE 8- MAX0 VSECONDARY VOLTAGE 8- MAX0 VSECONDARY VOLTAGE 9- MAX0 V		0 V
MAX0 VSECONDARY VOLTAGE 3 - MIN0 VSECONDARY VOLTAGE 4 - MAX0 VPRODUCT CATEGORYSingle-phase control transformers STSECONDARY VOLTAGE 4 - MIN0 VSECONDARY VOLTAGE 5 - MAX0 VSECONDARY VOLTAGE 5 - MIN0 VSECONDARY VOLTAGE 6 - MAX0 VSECONDARY VOLTAGE 6 - MIN0 VSECONDARY VOLTAGE 7 - MAX0 VSECONDARY VOLTAGE 7 - MAX0 VSECONDARY VOLTAGE 7 - MIN0 VSECONDARY VOLTAGE 8 - MAX0 VSECONDARY VOLTAGE 8 - MAX0 VSECONDARY VOLTAGE 8 - MAX0 VSECONDARY VOLTAGE 9 - MAX0 V		0 V
MIN0 VSECONDARY VOLTAGE 4- MAX0 VPRODUCT CATEGORYSingle-phase control transformers STSECONDARY VOLTAGE 4- MIN0 VSECONDARY VOLTAGE 5- MAX0 VSECONDARY VOLTAGE 6- MAX0 VSECONDARY VOLTAGE 7- MAX0 VSECONDARY VOLTAGE 7- MAX0 VSECONDARY VOLTAGE 8- MAX0 V		0 V
MAX0 VPRODUCT CATEGORYSingle-phase control transformers STSECONDARY VOLTAGE 4- MIN0 VSECONDARY VOLTAGE 5- MAX0 VSECONDARY VOLTAGE 5- MIN0 VSECONDARY VOLTAGE 6- MAX0 VSECONDARY VOLTAGE 6- MIN0 VSECONDARY VOLTAGE 6- MIN0 VSECONDARY VOLTAGE 6- MIN0 VSECONDARY VOLTAGE 7- MIN0 VSECONDARY VOLTAGE 7- MIN0 VSECONDARY VOLTAGE 8- MAX0 VSECONDARY VOLTAGE 8- MIN0 VSECONDARY VOLTAGE 9- MAX0 V		0 V
PRODUCT CATEGORYtransformers STSECONDARY VOLTAGE 4- MIN0 VSECONDARY VOLTAGE 5- MAX0 VSECONDARY VOLTAGE 5- MAX0 VSECONDARY VOLTAGE 6- MAX0 VSECONDARY VOLTAGE 6- MIN0 VSECONDARY VOLTAGE 6- MIN0 VSECONDARY VOLTAGE 7- MIN0 VSECONDARY VOLTAGE 7- MIN0 VSECONDARY VOLTAGE 7- MIN0 VSECONDARY VOLTAGE 8- MAX0 VSECONDARY VOLTAGE 8- MAX0 VSECONDARY VOLTAGE 8- MAX0 VSECONDARY VOLTAGE 9- MAX0 V		0 V
MIN 0 V SECONDARY VOLTAGE 5 - MAX 0 V SECONDARY VOLTAGE 5 - MIN 0 V SECONDARY VOLTAGE 6 - MAX 0 V SECONDARY VOLTAGE 6 - MIN 0 V SECONDARY VOLTAGE 6 - MIN 0 V SECONDARY VOLTAGE 7 - MAX 0 V SECONDARY VOLTAGE 7 - MIN 0 V SECONDARY VOLTAGE 7 - MAX 0 V SECONDARY VOLTAGE 8 - MAX 0 V SECONDARY VOLTAGE 8 - MAX 0 V SECONDARY VOLTAGE 8 - MIN 0 V SECONDARY VOLTAGE 9 - MAX 0 V	PRODUCT CATEGORY	
MAX Ο V SECONDARY VOLTAGE 5 - MIN Ο V SECONDARY VOLTAGE 6 - MAX Ο V SECONDARY VOLTAGE 6 - MIN Ο V SECONDARY VOLTAGE 7 - MAX Ο V SECONDARY VOLTAGE 7 - MIN Ο V SECONDARY VOLTAGE 7 - MIN Ο V SECONDARY VOLTAGE 8 - MAX Ο V SECONDARY VOLTAGE 8 - MIN Ο V SECONDARY VOLTAGE 8 - MIN Ο V SECONDARY VOLTAGE 8 - MIN Ο V SECONDARY VOLTAGE 9 - MAX Ο V		0 V
MIN0 VSECONDARY VOLTAGE 6 - MAX0 VSECONDARY VOLTAGE 6 - MIN0 VSECONDARY VOLTAGE 7 - MIN0 VSECONDARY VOLTAGE 7 - MIN0 VSECONDARY VOLTAGE 8 - MIN0 VSECONDARY VOLTAGE 9 - MAX0 V	SECONDARY VOLTAGE 5 -	0 V
MAXO VSECONDARY VOLTAGE 6 - MINO VSECONDARY VOLTAGE 7 - MAXO VSECONDARY VOLTAGE 7 - MINO VSECONDARY VOLTAGE 8 - MAXO VSECONDARY VOLTAGE 8 - MINO VSECONDARY VOLTAGE 8 - MINO VSECONDARY VOLTAGE 8 - MINO VSECONDARY VOLTAGE 9 - MAXO VSECONDARY VOLTAGE 9 - O VO V		
MIN0 VSECONDARY VOLTAGE 7 - MAX0 VSECONDARY VOLTAGE 7 - MIN0 VSECONDARY VOLTAGE 8 - MAX0 VSECONDARY VOLTAGE 8 - MIN0 VSECONDARY VOLTAGE 9 - MAX0 V	MAX SECONDARY VOLTAGE 5 -	0 V
MAXO VSECONDARY VOLTAGE 7 - MINO VSECONDARY VOLTAGE 8 - MAXO VSECONDARY VOLTAGE 8 - MINO VSECONDARY VOLTAGE 9 - 	MAX SECONDARY VOLTAGE 5 - MIN SECONDARY VOLTAGE 6 -	
MIN0 VSECONDARY VOLTAGE 8 - MAX0 VSECONDARY VOLTAGE 8 - MIN0 VSECONDARY VOLTAGE 9 - MAX0 VSECONDARY VOLTAGE 9 - O V0 V	MAX SECONDARY VOLTAGE 5 - MIN SECONDARY VOLTAGE 6 - MAX SECONDARY VOLTAGE 6 -	0 V
MAX 0 V SECONDARY VOLTAGE 8 - MIN 0 V SECONDARY VOLTAGE 9 - MAX 0 V SECONDARY VOLTAGE 9 - MAX 0 V	MAX SECONDARY VOLTAGE 5 - MIN SECONDARY VOLTAGE 6 - MAX SECONDARY VOLTAGE 6 - MIN SECONDARY VOLTAGE 7 -	0 V 0 V
MIN 0V SECONDARY VOLTAGE 9 - 0V SECONDARY VOLTAGE 9 - 0V	MAX SECONDARY VOLTAGE 5 - MIN SECONDARY VOLTAGE 6 - MAX SECONDARY VOLTAGE 6 - MIN SECONDARY VOLTAGE 7 - MAX SECONDARY VOLTAGE 7 -	0 V 0 V 0 V
MAX 0V SECONDARY VOLTAGE 9 - 0V	MAX SECONDARY VOLTAGE 5 - MIN SECONDARY VOLTAGE 6 - MAX SECONDARY VOLTAGE 6 - MIN SECONDARY VOLTAGE 7 - MAX SECONDARY VOLTAGE 7 - MIN	0 V 0 V 0 V 0 V
0 V	MAX SECONDARY VOLTAGE 5 - MIN SECONDARY VOLTAGE 6 - MAX SECONDARY VOLTAGE 6 - MIN SECONDARY VOLTAGE 7 - MIN SECONDARY VOLTAGE 7 - MIN SECONDARY VOLTAGE 8 -	0 V 0 V 0 V 0 V 0 V
	MAX SECONDARY VOLTAGE 5 - MIN SECONDARY VOLTAGE 6 - MAX SECONDARY VOLTAGE 6 - MIN SECONDARY VOLTAGE 7 - MAX SECONDARY VOLTAGE 7 - MIN SECONDARY VOLTAGE 8 - MAX SECONDARY VOLTAGE 8 - MIN	0 V 0 V 0 V 0 V 0 V 0 V

SHORT-CIRCUIT LOSSES	21 W
SHORT-TIME RATING	0.44 kVA
STATIC HEAT DISSIPATION, NON- CURRENT-DEPENDENT PVS	30 W
VOLTAGE RATING - MAX	600 V
POWER CONSUMPTION IN STANDBY MODE	9 W

PROJECT NAME:

PROJECT NUMBER:

PREPARED BY:

DATE:



Eaton Corporation plc Eaton House 30 Pembroke Road Dublin 4, Ireland Eaton.com

© 2025 Eaton. All Rights Reserved.

Follow us on social media to get the latest product and support information.

