



 PRODUCT-DETAILS

TRFM/400

TRFM/400 Current modular transformer



General Information

Extended Product Type	TRFM/400
Product ID	2CSM100140R1111
EAN	8012542047407
Catalog Description	TRFM/400 Current modular transformer
Long Description	Used to transform primary currents into .../5 A low secondary currents indirectly supplying power to analogue and digital measurement instrument devices. They have through primary and modular case and DIN rail fasten system.

Technical

Current Rating	400 A
Rated Primary Current (I_{pn})	400 A
Rated Secondary Current (I_{sn})	5 A
Current Limit Function	FS 5
Apparent Power Output	3 V·A
Secondary Output Connection	Screw connection
Model Number	Through-feed current converter

Number of Inputs	Primary 1
Mounting Type	DIN-Rail

Material Compliance

RoHS Information	9AKK106713A5716
RoHS Status	Following EU Directive 2011/65/EU and Amendment 2015/863 July 22, 2019
RoHS Date	20230928
Conflict Minerals Reporting Template (CMRT)	9AKK108468A3363

Environmental

Degree of Protection	IP20
Environmental Information	See RoHS Information

Dimensions

Product Net Width	0.065 m
Product Net Height	0.075 m
Product Net Depth / Length	0.100 m
Product Net Weight	0.181 kg
Bore Diameter	155 mm

Ordering

Package Level 1 Units	box 1 piece
Package Level 1 Gross Weight	0.78 kg
E-Number (Finland)	6701049

Certificates and Declarations

Declaration of Conformity - CE	9AKK106713A5716
--------------------------------	-----------------

Installation

Instructions and Manuals	No document needed
--------------------------	--------------------

Popular Downloads

Data Sheet, Technical Information	9AKK107046A0430
-----------------------------------	-----------------

Classifications

ETIM 8	EC002048 - Current transformer
ETIM 9	EC002048 - Current transformer
WEEE Category	5. Small Equipment (No External Dimension More Than 50 cm)
WEEE B2C / B2B	Business To Consumer

CN8	85043121
eClass	V11.0 : 27210902
Object Classification Code	T

Categories

Low Voltage Products and Systems → Modular DIN Rail Products → Energy Efficiency Devices → Current Transformers

