PSR45-600-11 1/5



PRODUCT-DETAILS

## PSR45-600-11

## PSR45-600-11 Softstarter - 45 A - 208 ... 600 V AC



<b>General Information</b>	
Global Commercial Alias	PSR45-600-11
Extended Product Type	PSR45-600-11
Product ID	1SFA896111R1100
ABB Type Designation	PSR45-600-11
EAN	7320500477229
Catalog Description	PSR45-600-11 Softstarter - 45 A - 208 600 V AC
	The softstarter PSR45-600-11 has a rated maximum operational current of 45 A with an operating voltage span from 208600 V AC. The rated control voltage is 24 V AC/DC. PSR features a two-phase control soft start and stop through a voltage ramp. It has built-in bypass for easy installation and energy saving. A RUN and a TOR signal is available from a relay output in NO (normally open state). The start/stop ramp and time is easy to set by three potentiometers on the front. PSR is often used in
Long Description	combination with a manual motor starter (MMS) from ABB, so mechanical connection kits are available. Another popular option is Fieldbus communication, which can be enabled by an external adaptor and a Fieldbus plug. The PSR range is our most compact softstarters with basic functionality and values. They are suitable for small

three-phase motors with nominal currents from 3...105 A and can manage up to 100 starts per hour. Common applications are, for example, pumps, fans, compressors,

and conveyors.

PSR45-600-11 2/5

Minimum Order Quantity	1 piece
Customs Tariff Number	8537109
Popular Downloads	
Data Sheet, Technical Information	1SFC132012C020
Instructions and Manuals	1SFC132078M990
CAD Dimensional Drawing	2CDC001079B0201
Wiring Diagram	N/A
Dimensions	
Product Net Width	153 mm
Product Net Height	187 mm
Product Net Depth / Length	54 mm
Product Net Weight	1 kg
Rated Operational Voltage	208 600 V AC
Voltage Rated Control Supply	24 V AC/DC
Voltage (U <sub>s</sub> ) Rated Control Circuit	
	24 V DC
Voltage (U <sub>c</sub> )	24 V DC
Voltage (U <sub>c</sub> ) Rated Frequency (f)	24 V DC 50/60 Hz Main Circuit 50 / 60 Hz
	50/60 Hz
Rated Frequency (f)  Rated Operational Power	50/60 Hz Main Circuit 50 / 60 Hz (230 V) 11 kW (400 V) 22 kW
Rated Frequency (f)  Rated Operational Power - In-Line Connection (Pe)  Rated Operational Current - In-Line	50/60 Hz Main Circuit 50 / 60 Hz (230 V) 11 kW (400 V) 22 kW (500 V) 30 kW
Rated Frequency (f)  Rated Operational Power - In-Line Connection (Pe)  Rated Operational Current - In-Line Connection (le)  Service Factor	50/60 Hz Main Circuit 50 / 60 Hz (230 V) 11 kw (400 V) 22 kw (500 V) 30 kw 45 A
Rated Frequency (f)  Rated Operational Power - In-Line Connection (Pe)  Rated Operational Current - In-Line Connection (Ie)  Service Factor Percentage Overload Protection Integrated Electronic	50/60 Hz Main Circuit 50 / 60 Hz (230 V) 11 kW (400 V) 22 kW (500 V) 30 kW 45 A
Rated Frequency (f)  Rated Operational Power - In-Line Connection (Pe)  Rated Operational  Current - In-Line  Connection (le)  Service Factor  Percentage  Overload Protection	50/60 Hz Main Circuit 50 / 60 Hz (230 V) 11 kW (400 V) 22 kW (500 V) 30 kW 45 A
Rated Frequency (f)  Rated Operational Power - In-Line Connection (Pe)  Rated Operational Current - In-Line Connection (Ie)  Service Factor Percentage Overload Protection Integrated Electronic Overload Adjustable Rated Motor	50/60 Hz Main Circuit 50 / 60 Hz (230 V) 11 kW (400 V) 22 kW (500 V) 30 kW 45 A

Initial Voltage During

Step Down Voltage Special Ramp

Connection

**Current Limit Function** 

Switch for Inside Delta

Start

No

No

40 ... 70 %

100 ... 60 %

PSR45-600-11 3/5

Run Signal Relay	Yes
By-pass Signal Relay	Yes
Fault Signal Relay	No
Overload Signal Relay	No
Signal Indication Completed Start Ramp (LED)	Green
Signal Indication Ready to Start/Standby ON (LED)	Greer
Signal Indication Running R (LED)	Greer
Signal Indication Ramping Up/Down (LED)	Green
Number of Starts Per Hour at 3.5*le for 7 sec. 50% ON Time 50% OFF Time	10
Communication	FiledBusPlug(Optional)
Degree of Protection	IP10
Terminal Type	Screw Terminals
Connecting Capacity Main Circuit	Rigid 1x 6 35 mm Rigid 2 x 6 16 mm
Connecting Capacity Control Circuit	1 x 0.75 2.5 2 x 0.75 2.5 mm Rigid 1/2 x 0.75 2.5 mm
Connecting Capacity Supply Circuit	Rigid 1 x 0.75 2.5 mm <sup>2</sup>
Tightening Torque	Control Circuit 0.6 N·m Main Circuit 8 N·m Supply Circuit 0.6 N·m
Product Main Type	PSR45
Function	Soft start with voltage ramp

Technical UL/CSA	
Maximum Operating Voltage UL/CSA	Main Circuit 600 V
Tightening Torque UL/CSA	Control Circuit 5.3 in·lb Main Circuit 70.8 Supply Circuit 5.3 in·lb

Environmental	
Ambient Air	Operation -25 +60 °C
Temperature	Storage -40 +70 °C
Degree of Protection	IP10

Material Compliance	
Conflict Minerals Reporting Template (CMRT)	9AKK108467A5658
REACH Declaration	2CMT2022-006481
RoHS Information	2CMT2022-006500
RoHS Status	Following EU Directive 2011/65/EU and Amendment 2015/863 July 22, 2019

PSR45-600-11 4/5

Toxic Substances Control Act - TSCA	2CMT2023-006524
WEEE B2C / B2B	Business To Business
WEEE Category	5. Small Equipment (No External Dimension More Than 50 cm)

Certificates and Declarations		
CQC Certificate	CQC2006010304208083	
Declaration of Conformity - CCC	2020980304001089	
Declaration of Conformity - CE	2CMT004861	

Container Information	
Package Level 1 Width	163 mm
Package Level 1 Depth / Length	56 mm
Package Level 1 Height	217 mm
Package Level 1 Gross Weight	1.1 kg
Package Level 1 EAN	7320500477229
Package Level 1 Units	box 1 piece

Classifications	
Object Classification Code	Q
ETIM 7	EC000640 - Soft starter
ETIM 8	EC000640 - Soft starter
ETIM 9	EC000640 - Soft starter
eClass	V11.0 : 27370907
UNSPSC	39121521
IDEA Granular Category Code (IGCC)	4740 >> Soft starter

Accessories				
Identifier	Description	Type Quantity		Unit Of Measure
1SFA896216R1001 PSR45-MS165 Conne		nection Kit PSR45-MS165 1		piece
1SFA896312R1002	PS-FBPA Fieldbus plug kit	PS-FBPA	1	piece
1SFA896311R1001	PSR-FAN3-45A FANPSR-F	AN3-45A	1	piece

PSR45-600-11 5/5

## Categories

 $Drives \rightarrow Softstarters \rightarrow PSR \ Softstarters \rightarrow PSR$ 





