PSR85-600-70 1/5



PRODUCT-DETAILS

PSR85-600-70

PSR85-600-70 Softstarter - 85 A - 208 ... 600 V AC



senerai intormatio	n
--------------------	---

Global Commercial Alias	PSR85-600-70
Extended Product Type	PSR85-600-70
Product ID	1SFA896114R7000
ABB Type Designation	PSR85-600-70
EAN	7320500362631
Catalog Description	PSR85-600-70 Softstarter - 85 A - 208 600 V AC

Long Description

The softstarter PSR85-600-70 has a rated maximum operational current of 85 A with an operating voltage span from 208...600 V AC. The rated control voltage is between 100...240 V AC at 50/60 Hz. PSR features a two-phase control soft start and stop through a voltage ramp. It has built-in bypass for easy installation and energy saving. A RUN and a TOR signal is available from a relay output in NO (normally open state). The start/stop ramp and time is easy to set by three potentiometers on the front. PSR is often used in combination with a manual motor starter (MMS) from ABB, so mechanical connection kits are available. Another popular option is Fieldbus communication, which can be enabled by an external adaptor and a Fieldbus plug. The PSR range is our most compact softstarters with basic functionality and values. They are suitable for small three-phase motors with nominal currents from 3...105 A and can manage up to 100 starts per hour. Common applications are, for example, pumps, fans, compressors, and conveyors.

PSR85-600-70 2/5

Ordering	
Minimum Order Quantity	1 piec
Customs Tariff Number	8537109.
Popular Downloads	
Data Sheet, Technical Information	1SFC132012C020
Instructions and Manuals	1SFC132033M000
CAD Dimensional Drawing	2CDC001079B020
Wiring Diagram	N/A
Dimensions	
Product Net Width	180 mm
Product Net Height	220 mm
Product Net Depth / Length	70 mn
Product Net Weight	2.1 kg
Technical	
Rated Operational	208 600 V AG
Voltage Rated Control Supply Voltage (U _S)	100 240 V AC
Rated Control Circuit Voltage (U _c)	24 V DO
Rated Frequency (f)	50/60 H: Main Circuit 50 / 60 H:
Rated Operational Power - In-Line Connection (Pe)	(230 V) 22 kv (400 V) 45 kv (500 V) 55 kv
Rated Operational Current - In-Line Connection (Ie)	85 /
Service Factor Percentage	100 %
Overload Protection	Recommended MS495 70 90
Integrated Electronic	No
Overload	

Starting Capacity at

Initial Voltage During

Step Down Voltage

Switch for Inside Delta

Special Ramp
Current Limit Function

Connection

le

Start

Ramp Time

Maximum Rated Current

No

No

4xle for 6s

40 ... 70 %

100 ... 60 %

0 ... 20 second [unit of time] 1 ... 10 second [unit of time] PSR85-600-70 3/5

Ye	Run Signal Relay
Ye	By-pass Signal Relay
No	Fault Signal Relay
No	Overload Signal Relay
Green	Signal Indication Completed Start Ramp (LED)
Green	Signal Indication Ready to Start/Standby ON (LED)
Green	Signal Indication Running R (LED)
Green	Signal Indication Ramping Up/Down (LED)
10	Number of Starts Per Hour at 3.5*le for 7 sec. 50% ON Time 50% OFF Time
FiledBusPlug(Optional	Communication
IP10	Degree of Protection
Main Circuit: Bars Rigid 1x 10 95 mm Rigid 2 x 6 35 mm	Terminal Type Connecting Capacity Main Circuit
1 x 0.75 2.5 2 x 0.75 2.5 mm Rigid 1 x 0.75 2.5 mm Rigid 2 x 0.75 1.5 mm	Connecting Capacity Control Circuit
Rigid 1 x 0.75 2.5 mm	Connecting Capacity Supply Circuit
Control Circuit 0.6 N·n Main Circuit 8 N·n Supply Circuit 0.6 N·n	Tightening Torque
PSR8	Product Main Type
Soft start with voltage ramp Soft stop with voltage ramp	Function
	Technical UL/CSA
Main Circuit 600 \	Maximum Operating Voltage UL/CSA
Main Circuit 600 \ Control Circuit 5.3 in-lk Main Circuit 70.8 Supply Circuit 5.3 in-lk	
Control Circuit 5.3 in lk Main Circuit 70.8	Voltage UL/CSA Tightening Torque
Control Circuit 5.3 in lk Main Circuit 70.8	Voltage UL/CSA Tightening Torque UL/CSA
Control Circuit 5.3 in·lk Main Circuit 70.8 Supply Circuit 5.3 in·lk Operation -25 +60 °C	Voltage UL/CSA Tightening Torque UL/CSA Environmental Ambient Air
Control Circuit 5.3 in·lk Main Circuit 70.8 Supply Circuit 5.3 in·lk Operation -25 +60 °C Storage -40 +70 °C	Voltage UL/CSA Tightening Torque UL/CSA Environmental Ambient Air Temperature
Control Circuit 5.3 in·lk Main Circuit 70.8 Supply Circuit 5.3 in·lk Operation -25 +60 °C Storage -40 +70 °C	Voltage UL/CSA Tightening Torque UL/CSA Environmental Ambient Air Temperature Degree of Protection
Control Circuit 5.3 in·lt Main Circuit 70.8 Supply Circuit 5.3 in·lt Operation -25 +60 °C Storage -40 +70 °C	Voltage UL/CSA Tightening Torque UL/CSA Environmental Ambient Air Temperature Degree of Protection Material Compliance Conflict Minerals Reporting Template

PSR85-600-70 4/5

RoHS Status	Following EU Directive 2011/65/EU and Amendment 2015/863 July 22, 2019	
Toxic Substances Control Act - TSCA	2CMT2023-006524	
WEEE B2C / B2B	Business To Business	
WEEE Category	5. Small Equipment (No External Dimension More Than 50 cm)	

Certificates and Declarations	
CQC Certificate	CQC2008010304295498
Declaration of Conformity - CCC	2020980304001090
Declaration of Conformity - CE	1SFA1-95

Container Information	
Package Level 1 Width	195 mm
Package Level 1 Depth / Length	86 mm
Package Level 1 Height	230 mm
Package Level 1 Gross Weight	2.3 kg
Package Level 1 EAN	7320500362631
Package Level 1 Units	box 1 piece

Classifications	
Object Classification Code	Q
ETIM 7	EC000640 - Soft starter
ETIM 8	EC000640 - Soft starter
ETIM 9	EC000640 - Soft starter
eClass	V11.0 : 27370907
UNSPSC	39121521
IDEA Granular Category Code (IGCC)	4740 >> Soft starter

Accessories				
Identifier	Description	Type Quantity		Unit Of Measure
1SFA899002R1072	PSLW-72 Terminal Enlargement	PSLW-72	1	piece
1SFA896312R1002	PS-FBPA Fieldbus plug kit	PS-FBPA	1	piece
1SFA896313R1001	PSR-FAN60-105A FAN	PSR-FAN60- 105A	1	piece

PSR85-600-70 5/5

Categories

 $\mathsf{Drives} \to \mathsf{Softstarters} \to \mathsf{PSR}\,\mathsf{Softstarters} \to \mathsf{PSR85}$

 $Low\ Voltage\ Products\ and\ Systems \rightarrow Control\ Products\ \rightarrow\ Softstarters\ \rightarrow\ PSR\ Sof$





