



Caratteristiche Costruttive

Esecuzione protetta per impiego indipendente
Impregnazione totale in vernice termoindurente
Lamierino a basse perdite
Fissaggio su profilato omega EN 50022
Grado di Protezione IP20
Classe Isolamento Termica F
Classe Elettrica di protezione II
Connessioni primario su morsetti da 2,5 - 4 mm²
Connessioni secondario in morsetti fino a 2 x 95mm²

Caratteristiche Tecniche

Tensione Primaria: 0.230.400V
Prese di regolazione al primario: $\pm 15V$
Tensione Secondaria:
115V con collegamento parallelo
230V (115.0.115V) con collegamento serie
Frequenza: 50-60Hz
Temperatura ambiente max: 40°C

Norme di riferimento

EN 61558-1
EN 61558-2-4



INSTALLAZIONE SU PROFILO
OMEGA EN50022 BARRA DIN

INSTALLATION ON PROFILE
OMEGA EN 50022 DIN RAIL

115VAC

PIENA POTENZA

230VAC

PIENA POTENZA

General Characteristics


Protected execution for independent use
Total impregnated with thermosetting varnish
Low losses magnetic sheet steel
Mounting on omega profile EN50022
Protection degree IP20
Thermal Insulation class F
Electric class protection II
Primary connections on terminals 2,5 - 4 mm²
Secondary connections on terminals 2x95 mm²

Technical Features

Primary Voltage: 0.230.400V
Regulation taps on primary: $\pm 15V$
Secondary Voltage:
115V with parallel connection
230V (115.0.115V) with series connection
Frequency: 50-60Hz
Max ambient temperature: 40°C

Reference standards

EN 61558-1
EN 61558-2-4



CODICE CODE	POTENZA POWER	PERDITE A VUOTO NO-LOAD LOSSES	PERDITE IN C.C. S.C.LOSSES	VCC on 400V.	PESO WEIGHT	DIMENSIONI (mm) DIMENSIONS (mm)				
(Art.)	(VA)	(W)	(W)	(%)	(KG)	(L)	(P)	(H)	(E)	(D)
EUI0025C230	25	3	3	6	1,6	90	106	96	69	91
EUI005C230	50	4	5	6	1,7	90	106	96	69	91
EUI0065C230	65	4	7	7	1,9	90	106	96	69	91
EUI010C230	100	6	10	8	2,5	90	106	106	69	91
EUI015C230	150	7	14	8	2,8	90	106	116	69	91
EUI020C230	200	10	14	5	4,6	126	136	114	96	120
EUI025C230	250	10	16	6	5,1	126	136	114	96	120
EUI030C230	300	13	18	5	5,2	126	136	124	96	120
EUI040C230	400	13	21	5,5	5,4	126	136	124	96	120

Connection 230Vac



Controllare i ponticelli metallici se posti nella condizione standard di fabbrica (posizione tra morsetto 2-3 lato secondario)
Prelevare la tensione tra i morsetti 1-4 lato secondario (potenza piena)
Check the metal jumpers if placed in the standard condition factory setting (position between terminal 2-3 secondary side)
Take the voltage between terminals 1-4 secondary side (full power)

Dati indicativi (le caratteristiche tecniche possono subire variazioni in base ai criteri dell'ufficio Ricerca e Sviluppo)
Indicative values (the technical information may vary according to the R&D criteria)

Connection 115Vac



Spostare i ponticelli metallici:
nr. 1 ponticello tra il morsetto 1-2 lato secondario
nr. 1 ponticello tra il morsetto 3-4 lato secondario
Prelevare la tensione tra i morsetti 1-4 lato secondario (potenza piena)
Move the metal jumpers:
nr. 1 jumper between terminal 1-2 on the secondary side
nr. 1 jumper between terminal 3-4 on the secondary side
Take the voltage between terminals 1-4 secondary side (full power)