Release date: 2024-12-17 Date of issue: 2024-12-17 Filename: 304276-001059_eng.pdf

Inductive sensor

NSB10-30GH50-2E2-M1-S2D2

- No unusable area
- 10 mm flush
- Use of standard metallic actuating surfaces
- Applications up to Cat. 2, PLd/SIL 2 possible (can be used redundantly up to Cat. 3, PLe/SIL 3)
- LED for switching state and fault indication
- Safety outputs OSSD
- E1-Type approval
- Extended temperature range -40 ... +85 °C
- TÜV certified
- 10 V DC ... 30 V DC supply voltage
- Max. altitude 5000 m












Function

The inductive safety sensors are TÜV-certified in accordance with the EU Machinery Directive, Performance Level PLd, Category 2, and SIL2. They are used to safeguard machines and plant components, as well as for reliable position detection in this environment. With their OSSD interface for reliable, redundant shutdown of electronic outputs, they enable easy connection to a safety PLC or fail-safe control interfaces. They can also be operated as standard sensors. The sensors reliably detect standard metal objects in front of the sensor face without coding or similar; there is no blind zone. High characteristic safety values allow longer testing intervals than comparable solutions with a microcontroller. 2 sensors can be connected with 2-channel redundancy and allow PLe as a Category 3 solution.

Dimensions



Technical Data

| General specifications | | |
|-------------------------------------|----|--|
| Switching function | | 2 x normally open (NO) |
| Output type | | PNP |
| Rated operating distance | Sn | 10 mm |
| Installation | | flush |
| Output polarity | | DC |
| Assured operating distance | Sa | 0 8.1 mm |
| Actuating element | | Reference target according EN IEC 60947-5-2 (FE360 - ST37K) 30 mm x 30 mm x 1 mm |
| Reduction factor r _{AI} | | 0.5 |
| Reduction factor r _{Cu} | | 0.45 |
| Reduction factor r ₃₀₄ | | 0.8 |
| Reduction factor r _{Brass} | | 0.55 |
| Output type | | 4-wire |

Technical Data **Nominal ratings** U_{B} 10 ... 30 V Operating voltage Rated operating voltage $U_{\rm e}$ 12 ... 24 V 0 ... 30 Hz Switching frequency Hysteresis Н typ. 5% Reverse polarity protection reverse polarity protected Short-circuit protection pulsing Overload resistance yes Voltage drop U_d ≤3 V at I_L (sum of all outputs) max. 50 mA $\mathsf{U}_{\mathsf{BIS}}$ Rated insulation voltage 30 V Operating current 1 ... 30 mA per output I_L Off-state current I_r 0 ... 0.5 mA No-load supply current I_0 ≤ 15 mA Time delay before availability ţ,, ≤ 300 ms Switching state indicator LED, yellow Error indicator LED, red Functional safety related parameters Safety Integrity Level (SIL) SIL 2 Performance level (PL) PL d Cat. 2 Category MTTF_d > 7500 a Mission Time (T_M) 20 a Diagnostic Coverage (DC) min. 60 % Assured release distance of a PDDB \textbf{S}_{ar} 15 mm Compliance with standards and directives Standard conformity EN IEC 60947-5-2:2007 EN IEC 60947-5-3:2013 EN ISO 13849-1:2015 Standards EN IEC 61508:2010 EN IEC 62061:2021 compatible with EN ISO 61131-2:2007 Typ 1, 2, 3 Approvals and certificates **UL** approval cULus Listed, General Purpose, Class 2 Power Source CCC approval CCC approval / marking not required for products rated ≤36 V E1 Type approval 10R-06 **Ambient conditions** -40 ... 85 °C (-40 ... 185 °F) Ambient temperature Storage temperature -40 ... 85 °C (-40 ... 185 °F) Altitude ≤ 5000 m above MSL **Mechanical specifications** Connection type cable Housing material Stainless steel 1.4404 / AISI 316L PBT Sensing face Degree of protection IP68 / IP69 Cable Wire end ferrules yes Cable diameter 4.8 mm ± 0.15 mm Bending radius > 10 x cable diameter **PUR**

Length


Material Color

Number of cores Core cross section black

0.5 mm² 2 m

| Technical Data | | |
|---------------------|----------------------|--|
| Mass | 173 g | |
| Dimensions | | |
| Length | 65 mm | |
| Diameter | 30 mm | |
| General information | | |
| Scope of delivery | Supplied with 2 nuts | |

Connection



Commissioning

Note for Setting the Safety Control
The sensor has a self-monitoring function for the outputs. Therefore, to avoid any malfunctions of the sensor, deactivate all test pulses of the connected safety controller to the sensor.