

PNOZ e1.1p 24VDC 2so

774133



Safety relay (standalone) Inputs: 1-/2-channel wiring with/without detection of shorts across contacts Outputs: 2 safety outputs + 1 auxiliary output in semiconductor technology Automatic/monitored start, UB 24 V DC, width: 22.5 mm, plug-in Terminals of screw type, connecting several devices, Monitoring E-STOP, safety gates.

Dati tecnici

Omologazioni:	CE;cULus Listed;TÜV
Possibilità applicative:	Controllo ripari mobili;Controllo interruzione di emergenza istantaneo;Finecorsa;Controllo barriera fotoelettrica Tip. 4;Controllo barriera fotoelettrica Tip. 2 o T;Controllo barriera fotoelettrica Tip. 2 m T
Modalità operative:	monocanale;Start automatico;bicanale;Riconoscimento del cortocircuito;Test di avvio;Start manuale controllato;senza riconoscimento del cortocircuito;Autotest;con ingresso AND;con ingresso OR
Norma prodotto:	EN 60947-5-1
Norme:	DIN V VDE 801-1/A1;EN 60204-1;EN 62061;EN ISO 13849-1;VDE 0113-1;VDE 0116
Tensione di alimentazione (V):	24,0
Tipo di tensione di alimentazione:	DC
Tipo morsetto:	Morsetto a vite
Tipo morsetto:	estraibile
N. uscite di sicurezza istantanee:	2 ST
Numero di uscite di trigger:	2
Categoria di arresto:	0
Larghezza:	22.5 mm
Altezza:	94.0 mm
Profondità:	121.0 mm
Peso lordo:	145 g
Peso netto:	130 g

Temperatura ambiente:

-10 - 55 °C

Accessori opzionali



374280

PNOZ X Set plug in screw terminals P1+P2



774195

Terminal block filter 1



774196

Terminal block filter 2



874130B

PNOZelog Driver CD