



Televes si riserva il diritto di modificare il prodotto e/o specifiche tecniche indicate

Centrale larga banda MiniKom F

4 ingressi: FM-BIII/DAB-UHF-UHF

Centrale d'amplificazione da 4 ingressi (FM-BIII/DAB-UHF-UHF) per sistemi MATV. L'amplificazione separata garantisce l'assenza di intermodulazione tra gli ingressi e gli attenuatori indipendenti.

Art.539201

ID.NR	MVN437
EAN13	8424450144107

Si distingue per

- Amplificazione separata che migliora il livello di uscita senza causare interferenze tra le bande
- Attenuatori di guadagno ad ogni ingresso (0-20 dB), con tecnologia di diodi PIN
- Guadagno configurabile tramite un interruttore (alto/basso) e alto livello d'uscita
- Telaio ad alta schermatura, costruito in Zamak

Caratteristiche principali

- Connettori F
- LED indicatore di segnale in uscita
- Uscita test (-30 dB)
- Switch per l'alimentazione di preamplificatori o sistemi BOSS
- Avvitabile a parete

Caratteristiche tecniche

Inputs		Band	FM	BIII/DAB	UHF1	UHF2							
Frequency range		MHz	88-108	174-400	470-862	470-862							
Gain (low/high)		dB	15	20/30	27/37	27/37	Gain adjustment range		dB	0-20	0-20	0-20	0-20
Output level	DIN45004B (low/high)		dB μ V	112/114		116/117							
	EN50083	IMD3 (low/high)		109/111		113/114							113/114
		IMD2		103		-							-
Noise figure (Low/High)		dB	9	6,5/7	8/9,5	8/9,5							
Power on inputs		Vdc	-	12	12	-							
Max current through inputs		mA	-	70	70	-							
AC Power consumption		W	9										