pizzato

Illuminated button spring-return

Illuminated button spring-return

Emergency push button

Options

	Connection	
	A1	Supply input +24 Vdc
	A2	Supply input 0 Vdc
	IS1	Safety input
	OS1	Safety output
	IS2	Safety input
Safety switch	OS2	Safety output
	IE1	Solenoid activation input for double channel mode
	IE2	Solenoid activation input for double channel mode
	O3	Signalling output, actuator inserted
	O4	Signalling output, actuator inserted and locked
	I3	Actuator programming input / reset
	I5	EDM input (a)
	I4	Solenoid activation input for single channel mode

(a) Available for NS •5••1•••-N••• version only

	Contacts	Diagram
Device 1	1NO	B1—B4 / B2—B3 LED
Device 2	1NO	B1—B5 / B6—B3 LED
Device 3	2NC	B8—B9 / B10—B11

Connections

A1 — A1
A2 — A3
IS1 — A2
OS1 — A4
IS2 — A6
OS2 — A7
IE1 — A10
IE2 — A12
O3 — A5
O4 — A9
I3 — A8
I5 — A11

B1
B4
B5
B7
B8
B9
B10
B11
B2
B6
B12
0 V — B3

Connector	Double M12 with 12 pole at the bottom	