

E2N/MS20003pWMPnew



E2N/MS 2000 3p W MP new



General Information

Extended Product Type	E2N/MS20003pWMPnew
Product ID	1SDA058965R1
EAN	8015644613242
Catalog Description	E2N/MS 2000 3p W MP new
Long Description	SACE EMAX MOVING PART FOR C.BREAKER SWITCH-DISCONNECTOR E2N/MS 2000A THREE-POLE NEW

Ordering

EAN	8015644613242
Minimum Order Quantity	1 piece
Customs Tariff Number	85362090

Dimensions

Product Net Width	324 mm
Product Net Height	461 mm
Product Net Depth / Length	396.5 mm
Product Net Weight	49 kg

Container Information

Package Level 1 Units	1 piece
Package Level 1 Width	515 mm
Package Level 1 Height	600 mm
Package Level 1 Depth / Length	515 mm
Package Level 1 Gross Weight	59 kg
Package Level 1 EAN	8015644609139

Additional Information

Current Type	AC
Electrical Durability	10000 cycle 30 cycles per hour
Mechanical Durability	25000 cycle 60 cycles per hour

Number of Poles	3
Power Loss	330 W
Product Main Type	SACE Emax
Product Name	Switch Disconnecter
Product Type	Air Circuit Breaker
Rated Current (I_n)	2000 A
Rated Voltage (U_r)	690 V
Rated Impulse Withstand Voltage (U_{imp})	12 kV
Rated Insulation Voltage (U_i)	1000 V
Rated Operational Current (I_e)	2000 A
Rated Operational Voltage	690 V AC 250 V DC
Rated Short-time Withstand Current (I_{cw})	for 1 s 55 kA for 3 s 42 kA
Rated Uninterrupted Current (I_u)	2000 A
Standards	IEC
Sub-type	E2
Terminal Connection Type	Withdrawable Circuit-Breakers
Version	W

Certificates and Declarations (Document Number)

Data Sheet, Technical Information	1SDC200006D0209
Declaration of Conformity - CE	1SDL000165R0014
Environmental Information	1SDL000142R0
Instructions and Manuals	1SDH000460R0002

Classifications

ETIM 4	EC000228 - Power circuit-breaker for trafo/generator/installation prot.
ETIM 5	EC000228 - Power circuit-breaker for trafo/generator/installation prot.
ETIM 6	EC000216 - Switch disconnecter
Object Classification Code	Q
UNSPSC	39120000
WEEE Category	5. Small Equipment (No External Dimension More Than 50 cm)

Categories

Low Voltage Products and Systems → Circuit Breakers → Air Circuit Breakers → Emax

