CT120/1200 1/3



PRODUCT-DETAILS

CT120/1200

CT120/1200 Split core current transformer



General Information	
Extended Product Type	CT120/1200
Product ID	2CSG401200R1101
EAN	8012542889502
Catalog Description	CT120/1200 Split core current transformer
Long Description	CT120/1200 is a split core current transformer used to transform primary currents to/5A secondary currents for c.a. measurement instruments

Technical	
Cable Use	Vertical bar
Rated Primary Current (I pn)	1200 A
Rated Secondary Current (I _{sn})	5 A
Current Limit Function	FS 5
Frequency (f)	50 60 Hz
Apparent Power Output	5 V-A
Power Loss	10.3 V·A

CT120/1200 2/3

Secondary Output Connection	Screw connection
	
Accuracy	±0,5%
Model Number	Through-feed current converter
Number of Inputs	Primary 1
Mounting Type	Through Primary
Rated Cross-Section	4 x 120 x 10 mm

Material Compliance	
RoHS Information	2CSC445004K0901
RoHS Status	Following EU Directive 2002/95/EC August 18, 2005 and amendment
RoHS Date	03/04/2006 0.00.00
Conflict Minerals Reporting Template (CMRT)	9AKK108468A3363

Environmental	
Ambient Air	Operation -25 50 °C
Temperature	
Degree of Protection	IP20
Environmental	See RoHS Information
Information	

Dimensions	
Product Net Width	0.155 m
Product Net Height	0.198 m
Product Net Depth / Length	0.034 m
Product Net Weight	1.300 kg
Bore Diameter	0 mm

Ordering	
Package Level 1 Units	box 1 piece
Package Level 1 Gross Weight	1.3 kg

Certificates and Declarations	
Declaration of Conformity - CE	9AKK106713A5700
comoning ce	

Installation	
Instructions and	2CSC446012B0201
Manuals	

Popular Downloads

CT120/1200 3/3

Data Sheet, Technical 9AKK107046A0430 Information

Classifications	
ETIM 8	EC002048 - Current transformer
ETIM 9	EC002048 - Current transformer
WEEE Category	5. Small Equipment (No External Dimension More Than 50 cm)
WEEE B2C / B2B	Business To Consumer
CN8	85043121
eClass	V11.0 : 27210902
Object Classification	Ţ
Code	

Categories

 $Low\ Voltage\ Products\ and\ Systems \rightarrow Modular\ DIN\ Rail\ Products \rightarrow Energy\ Efficiency\ Devices \rightarrow Current\ Transformers$

