N2160.8 BL 1/3



PRODUCT-DETAILS

N2160.8 BL

Dimmer White - Zenit



General Information	
Extended Product Type	N2160.8 BL
Product ID	2CLA216080N1101
EAN	8427238229621
Catalog Description	Dimmer White - Zenit
Long Description	Color: White. Rated voltage: 127 Vac ± 10%. Frequency: 60 Hz. Power (min./max load): L-mode: - LEDi (leading-edge): 2 / 70 W/VA (max. 10 lamps). T-mode: - LEDi (trailing-edge): 2 / 180 W/VA (max. 10 lamps) LV LEDi with 12V transformer (L or LC): 2 / 180 W/VA (max. 10 lamps) Incandescent lamps: 2 / 180 W/VA Halogen lamps: 2 / 180 W/VA. *Max. 10 lamps. Load selection 2 or 3 wire connection. OFF position Electronic back-up fuse & overload protection. Size: 1 module.

N2160.8 BL 2/3

Installation	
Instructions and Manuals	2CLX216039A100
Mounting Type	Flush mounted (plaster
Type of Fastening	Snapper Mounting
 Technical	
	9AKK10103A5108
Data Sheet, Technical Information	9AKKIUIU3ASIU
Actuator Type	Turn butto
Connection Type	Screv
Number of Batteries	
 Electrical	
Rated Voltage (U _r)	110 127 \
Frequency (f)	60 60 H:
Load Type	Resistive load
Control Supply Voltage	110
Design	
Design Range	Zeni
Surface Finishing	Untreated Glossy
Material	Plasti Thermoplastic
RAL Number Color	RAL 9010 - Pure White
Material Compliance	
RoHS Information	2CLC216080N110
RoHS Status	Following EU Directive 2011/65/EU and Amendment 2015/863 July 22, 201
Conflict Minerals Reporting Template (CMRT)	9AKK108468A3363
 Environmental	
Degree of Protection	IP2(
Environmental Information	9AKK108466A4744
Dimensions	
Product Net Width	23.000 mn
Product Net Height	44.000 mn
Product Net Depth / Length	37.000 mn

Built-In Depth (t₂)

38 mm

N2160.8 BL 3/3

Ordering	
Replaced Product ID	2CLA216080N1102
(OLD)	2CLA216080N1103

Certificates and Declarations

Declaration of No declaration needed Conformity - CE

Classifications

ETIM 9	EC000025 - Dimmer
UNSPSC	39122206
WEEE Category	5. Small Equipment (No External Dimension More Than 50 cm)
WEEE B2C / B2B	Business To Consumer

Categories

 $Low\ Voltage\ Products\ and\ Systems \rightarrow Wiring\ Accessories\ -\ Light\ Switch\ Ranges \rightarrow Cover\ Plates\ and\ Control\ Elements \rightarrow Electronic\ Controls$





