SCHEDINA TECNICA - Z-MG/WAK80



Trasduttore, 80/5A 3 K., 2VA

Tipo Z-MG/WAK80 Catalog No. 101622



Abbildung ähnlich

Dati tecnici secondo ETIM 6.0

Low-voltage industrial components (EG000017) / Current transformer (EC002048)			
Electric engineering, automation, process control engineering / Signal processing / Transformer / Current transformer (ecl@ss8.1-27-21-09-02 [AAB626011])			
Model			Through-feed current converter
Primary rated current	Α	4	80
Secondary rated current	А	A	5
Secondary rated apparent power	V	/A	0
Accuracy class			3
Over voltage limiting factor			FS 5
Calibrated			No
With shock protection			No
Opening height	n	nm	0
Opening width	n	nm	0
Opening diameter	m	nm	22
Snap mounting			Yes
With copper rail			No
Secondary connection			Plug-in connection
Number of primary inputs			1
Number of primary inputs			1