DATA SHEET

 $\mathsf{EPIC}^{\scriptscriptstyle{\circledR}} \, \mathsf{SIGNAL} \,\, \mathsf{M23} \,\, \mathsf{12E/12P} \,\, \mathsf{D}\text{-}\mathsf{SUB}$



Description

Valid from: 17.09.2018

- Inserts for M23 circular connectors
- Efficient assembling due to the use of D-Sub contacts-on-reel



General characteristics

Series SIGNAL M23

Version E-part = rotation to the right (clockwise) /

P-part = rotation to the left (anticlockwise)

Number of contacts 12

Termination method Crimp termination Termination cross-section $0.08 - 0.56 \text{ mm}^2$ Temperaturbereich $-25 \text{ to } +125 \text{ }^{\circ}\text{C}$

Contacts included no

Product variations

Article no.	Version	Suitable contacts	PU
44420120	E-Part	male D-Sub crimp-contacts on reel	5
44420121	E-Part	male D-Sub crimp-contacts on reel	20
44420122	E-Part	female D-Sub crimp-contacts on reel	5
44420123	E-Part	female D-Sub crimp-contacts on reel	20
44420124	P-Part	male D-Sub crimp-contacts on reel	5
44420125	P-Part	male D-Sub crimp-contacts on reel	20
44420126	P-Part	female D-Sub crimp-contacts on reel	5
44420127	P-Part	female D-Sub crimp-contacts on reel	20

Mechanical characteristics

Cycles of mechanical operation 50

Electrical characteristics

Rated voltage, IEC 100 V
Rated impulse voltage 1,5 kV
Rated current 4 A
Contact resistance < 4 mOhm

Pollution degree 3

Materials and surfaces

Insert

Standards

Safety Standard IEC61984

Creator: MANA2/PDP	Document: DB44420120EN	Dago 1 of 2
Released: IVSE1/PDP	Version: 02	Page 1 of 3

Valid from: DATA SHEET


$\mathsf{EPIC}^{\mathrm{@}}\,\mathsf{SIGNAL}\,\,\mathsf{M23}\,\,\mathsf{12E/12P}\,\mathsf{D}\text{-}\mathsf{SUB}$




Technical Drawings

17.09.2018











Good chemical resistance



Industrial machinery and plant engineering



Mechanical resistance



Assembly time



Robust



Wind Energy



Variety of approval certifications

Creator: MANA2/PDP Document: DB44420120EN Page 2 of 3

Released: IVSE1/PDP Version: 02

Valid from: DATA SHEET

EPIC® SIGNAL M23 12E/12P D-SUB



Info

17.09.2018

For D-Sub ribbon contacts

Application range

Plant engineering Measurement and control technology Apparatus construction

Remark

The inserts are suitable for both male and female contacts. For a complete connection, you will need one P-component and one E-component. P-component = left turning (anticlockwise), E-component = right turning (clockwise)

Photographs are not to scale and do not represent detailed images of the respective products.

Creator: MANA2/PDP	Document: DB44420120EN	Dogo 2 of 2
Released: IVSE1/PDP	Version: 02	Page 3 of 3